

STEREO INTEGRITY DRIVER LIST

Driver	Re	Z	Le	Fs	Qms	Qes	Qts	BL	Mms	Vas	Sd	Xmax	Watts	SPL
	Ohms	Ohms	mH	Hz					g	Liters	cm^2	mm	RMS	1W/1M
Mag D2 v1/v2 12"	3.6	4	4.6	32	4.05	4.1	0.37	18.6	175.7	38.5	480	24	1000	88.4
Mag D2 v2 15"	3.7	4	4.6	29.6	4.38	0.41	0.379	21.5	227	147	810	24	1000	91.5
Mag D2 v3 12"	3.5	4	3.5	30.2	4.7	0.45	0.41	18.35	228	39.7	480	25	1000	85.7
Mag D2 v3 15"	3.7	4	3.7	22	3.7	0.39	0.35	18.35	262	184	810	25	1000	88.8
Mag D2 v4 12"	3.9	4	0.8	29	4.08	0.49	0.44	14	135.9	75	490	20	1000	87.6
BM D4 v1 10"	7.8	8	3.4	27.1	3.08	0.31	0.29	21.7	101	52.5	303	16	600	87.4
BM D4 v1 12"	7.8	8	3.4	28.3	3.55	0.38	0.34	21.9	128	83.6	480	16	600	88.8
BM mkIII 12"	6.1	8	2.4	15.8	5.22	0.41	0.38	19.6	263	130.5	490	14	450	82.9

Notes

All drivers measured with coils in series.

For individual coil Le, divide the above figures by 2.
 For instance, if Le is listed as 4.6, each coil has an inductance of 2.3. For parallel operation, divide the Le figure above by 4. For instance, if Le is listed as 4.6 above, the driver actually has an inductance of 1.15 when wired in parallel.